

JC13 Rec'd PCT/PTO 0 1 APR 2002

Description

METHOD FOR IDENTIFICATION OF AN OSCILLATION IN AN
ELECTRICAL POWER SUPPLY SYSTEM

5 CLAIM FOR PRIORITY

This application claims priority to International Application No. PCT/DE00/03434 which was filed in the German language on September 27, 2000.

10 TECHNICAL FIELD OF THE INVENTION

The invention relates to a method for producing at least one signal (oscillation signal), which indicates an oscillation in an electrical power supply system, in which method the phase current and the phase voltage are in each case sampled from at least one phase of the power supply system, forming phase current and phase voltage sample values, impedance values are formed from the phase current and phase voltage sample values, the impedance values are monitored for the presence of any oscillation and, if an oscillation is identified, at least one memory element is set, and the oscillation signal is output at its output, after setting the memory element, further impedance values are checked to determine whether the oscillation that has been found is still continuing, the memory element remains uninfluenced if the oscillation continues, and the memory element is reset if the oscillation has stopped.

BACKGROUND OF THE INVENTION

30 A method such as this is described in German Laid-Open Specification DE 195 03 626 A1 describes a method of identifying an oscillation. In this method, once a memory element has been set, further impedance values are checked to determine whether the oscillation that has been found is still continuing, by determining the rate of change of the magnitude of respectively successive impedance values and, if. If it is found that the rate of change is above a limit value, this identifies that the oscillation has stopped, and the

memory element is reset. It ~~has been found to be~~ is difficult to define such a limit value, particularly when a large number of generators are connected in the power supply networks, and complex oscillations can
5 thus occur.

SUMMARY OF THE INVENTION

The invention relates to a method for producing at least one signal (oscillation signal), which indicates
10 an oscillation in an electrical power supply system, in which method the phase current and the phase voltage are in each case sampled from at least one phase of the power supply system, forming phase current and phase voltage sample values, impedance values are formed from
15 the phase current and phase voltage sample values, the impedance values are monitored for the presence of any oscillation and, if an oscillation is identified, at least one memory element is set, and the oscillation signal is output at its output, after setting the
20 memory element, further impedance values are checked to determine whether the oscillation that has been found is still continuing, the memory element remains uninfluenced if the oscillation continues, and the
memory element is reset if the oscillation has stopped.

25 The invention ~~is based on the object of specifying~~ specifies a method of detecting ~~by means of which the~~ oscillation behavior of an electrical power supply system ~~can be detected safely and reliably at all times~~
30 in a safe and reliable manner.

For a method of the type mentioned initially, this object ~~is achieved according to~~ In one embodiment of the invention, there is a method ~~in that the checks of~~
35 the ~~further~~ impedance values and makes use of an oscillation model which is formed from previous impedance values associated with the oscillation, or from variables which are dependent on these impedance values; ~~avalues.~~ A check is then carried out to

determine whether a further impedance value formed at that time or a variable which is dependent on ~~this~~the further impedance value differs from the oscillation model, and any occurrence of a further impedance value or of a variable dependent on this impedance value which differs from the oscillation model is assessed as the oscillation having stopped.

~~One major~~ One advantage of the method according to the invention is that the oscillation model allows even complex oscillations to be described, and it is thus possible to identify that the oscillation has stopped with a high level of reliability even in the case of such complex oscillations.

 The oscillation model can advantageously be determined by means of a least squares estimation method. This estimation method allows a mathematical oscillation model to be produced from successive impedance values which have been formed after the setting of the memory element, that is to say after the start of the oscillation.

 A function in the form $f(x) = ax^3 + bx^2 + cx + d$ with the parameters a , b , c and d can be used as the model rule for ~~this~~the oscillation model, in which one or more parameters can be defined to be zero before the start of the estimation method. First, second or third order power functions can ~~thus~~ be used as the model rule. Furthermore, a sum of sine and cosine functions, which decay with time, can be used as the model rule for the oscillation model. These model rules make it possible to describe even complex oscillations mathematically.

 The oscillation model can be formed directly for the determined impedance values of the oscillation, or else for variables dependent on these impedance values. Resistance values R , reactance values X , time derivative values dZ/dt of the impedance, time

derivative values dR/dt of a resistance or time derivative values dx/dt of a reactance can be used as dependent variables. Choice of the most suitable variable for the oscillation model makes it possible to
5 determine with a high level of reliability that the oscillation has stopped, with the choice of the variable being dependent on the individual system configuration of the electrical power supply system.

10 _____ In one advantageous embodiment of the invention, positive phase sequence system impedance values can be formed from the phase current and phase voltage sample values, and a common memory element can be provided, and a common oscillation signal can be produced, for all
15 the phases in the power supply system. This variant can be used when the aim is to make a statement relating to any oscillation occurring at the same time in all the phases in the power supply system.

20 _____ In a further advantageous embodiment of the method according to the invention, phase impedance values are formed from the phase current and phase voltage sample values of each phase of the power supply system to be investigated for oscillation, and a dedicated memory
25 element is provided, and a dedicated oscillation signal is produced, for each of these phases. In this embodiment, the oscillation response of each individual phase in the power supply system can be investigated separately, ~~that is to say~~ separately. That is, both
30 the starting and the stopping of an oscillation are identified. This is particularly advantageous when oscillations occur in only a single phase, but not in all the phases, in the power supply system. Oscillations such as these frequently occur in the case
35 of so-called single-pole pauses in high-voltage systems. Single-pole pauses are produced by single-pole conductor ground faults, which can be expected frequently in high-voltage systems, and in which an arc is struck between one conductor and ground. In this

type of fault, a single-pole pause is ~~produced that is~~
to ~~say~~ produced. That is, the single phase in which the
single-pole conductor-ground fault has occurred is
switched off briefly. The arc is thus quenched, and the
5 fault is frequently corrected. Switching off a single
pole of one phase can result in oscillations occurring
in the remaining phases which are not switched off.
These oscillations cannot be identified, for example,
by monitoring the positive phase sequence system
10 impedance values, since positive phase sequence system
impedance values can ~~be~~ be formed only when sample
values are available for all the phases in the power
supply system. In the case of a single-pole pause, it
is ~~now~~ highly advantageous to be able to produce a
15 dedicated oscillation signal for each phase in the
power supply ~~system, during~~ system. During the single-
pole pause, this oscillation signal is produced ~~only~~ for
those phases which are not switched off. The
oscillation behavior of the power supply system can
20 thus be determined individually for each phase, and
independently of the state of the other phases.

 The phase impedance values of the individual
phases in the electrical power supply system can, for
25 example, be formed by, in order to form the phase
impedance values,

- a variable U_{re} ~~containing~~ including the real part
of the phase voltage sample values, a variable U_{im}
~~containing~~ including the imaginary part of the phase
30 voltage sample values, a variable I_{re}
~~containing~~ including the real part of the phase current
sample values and a variable I_{im} ~~containing~~ including
the imaginary part of the phase current sample values
being formed from the phase current and phase voltage
35 sample values (i, u) for each phase,

- a phase real power variable P being determined
from $P = U_{re} \cdot I_{re} - U_{im} \cdot I_{im}$,
- a phase wattless component variable Q being
determined from $Q = U_{im} \cdot I_{re} + U_{re} \cdot I_{im}$,

- a squared phase current amplitude variable I^2 being determined from $I^2 = I_{re} \cdot I_{re} + I_{im} \cdot I_{im}$,
- system-frequency components in each case being removed by means of least squares estimation method from the phase real power variable P , from the phase wattless component variable Q and from the squared phase current amplitude variable I^2 , and
- phase resistance values R being determined from $R=P/I^2$ and phase reactance values X being determined from $X=Q/I^2$, and phase impedance values $Z=R+jX$ being thus determined.

When forming the phase impedance values, it is particularly advantageous to remove the system frequency components (for example 50 Hz components) from the phase real power variable P , from the phase wattless component variable Q and from the squared phase current amplitude variable I^2 by means a least squares estimation method in each case. Such system frequency interference components would adversely affect the evaluation of the phase impedance values determined from these variables.

BRIEF DESCRIPTION OF THE DRAWINGS

In order to explain the invention further, Figure 1 shows a block diagram of an exemplary embodiment of the method according to the invention. ~~invention, Figure 2~~ Figure 2 shows a block diagram for determining the phase impedance values, ~~values.~~

Figure 3 shows the impulse response of the filters used for impedance ~~determination,~~ determination.

Figure 4 shows the real power and wattless component variable profiles before ~~filtering,~~ and filtering.

Figure 5 shows the real power and wattless

component variable profiles after filtering.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

Figure 1 shows, schematically, a method for determining the oscillation behavior of a three-phase electrical power supply system, by means of which a dedicated oscillation signal Pd1, Pd2 and Pd3 is produced for each phase in the power supply system. This is done by providing three changeover switches U1, U2 and U3 and three memory elements Spi, Sp2 and ~~Sp3~~, ~~the~~Sp3. The connecting lines between the individual units in the layout are designed with three poles. The phase current and phase voltage sample values i and u of all three phases are supplied to a unit for impedance determination Ib, at whose output phase impedance values Z are output for the three phases. These phase impedance values Z are supplied via the changeover switches U1, U2 and U3 to an oscillation identification unit Pe. The oscillation identification unit Pe uses the time profiles of the phase impedance values Z to identify the occurrence of any oscillation in the individual phases, for example in phase 1, and emits an oscillation set signal Ps at its output for each phase in which oscillation is identified, for example for the phase 1. The oscillation set signal Ps sets the memory element associated with the respective phase, for example Sp1, and this memory element emits at its output the phase-specific oscillation signal, for example, Pd1. When an oscillation signal is being emitted, for example the oscillation signal Pd1, the changeover switch, for example U1, associated with the respective phase is switched over. The phase impedance values Z which are still formed for the phase in which the oscillation has been identified, for example the phase 1, are supplied to an oscillation signal resetting unit Pü. This oscillation signal resetting unit Pü identifies that the oscillation has stopped and, in this case, emits an oscillation reset signal Pr at its output, which resets the memory element for the

respective phase, for example Sp1. The oscillation signal for the respective phase, for example Pd1, is thus also no longer emitted, and the respective changeover switch, for example U1, moves back to its original position once again. In response to a stimulus, a unit for phase selection Pa ensures that the phase impedance values of the phases to be investigated for oscillation are in each case processed by the oscillation identification unit Pe and by the oscillation signal resetting unit Pü.

____ The method of operation of the four units comprising impedance determination Ib, the oscillation identification unit Pe, the oscillation signal resetting unit Pü and phase selection Pa will be explained in more detail in the following text.

____ As shown in Figure 2, the phase current and phase voltage sample values i and u are filtered in the impedance determination unit Ib by means of orthogonal FIR filters F1, F2, F3 and F4, thus resulting in the production of a variable U_re containing the real part of the phase voltage sample values, a variable U_im containing the imaginary part of the phase voltage sample values, a variable I_re containing the real part of the phase current sample values, and the variable I_im containing the imaginary part of the phase current sample values.

____ Figure 3 shows the impulse responses of the filters F1 to F4, with the impulse response of the filters F1 and F3 which determine the real parts being annotated "o", and the impulse response of the filters F2 and F4 which determine the imaginary parts, being annotated "+".

____ As shown in Figure 2, following this, a phase real power variable P is calculated in accordance with equation (1) below and a phase wattless component

variable Q is calculated in accordance with equation (2) in the unit 5, and a squared phase current amplitude variable I^2 is calculated in accordance with equation (3) in the unit 6.

5

$$P = U_{re} \cdot I_{re} - U_{im} \cdot I_{um} \quad (1)$$

$$Q = U_{im} \cdot I_{re} + U_{im} \cdot I_{re} \quad (2)$$

$$I^2 = I_{re} \cdot I_{re} + I_{im} \cdot I_{im} \quad (3)$$

After this, the phase real power variable P, the phase wattless component variable Q and the squared phase current amplitude variable I^2 are filtered in units 7 and 8 in order to remove the interference 50 Hz components contained in these variables; this results in the filtered variables P', Q' and I'^2 . The least squares estimation method used for this filtering will be explained in detail further below.

15

The upper illustration a) in Figure 4 shows the profile of the real power variable P, and the lower illustration b) shows the profile of the Wattless component variable Q, before filtering by means of the least squares estimation method, in each case plotted against the time t.

The upper illustration a) in Figure 5 shows the profile of the real power variable P', and the lower illustration b) shows the profile of the Wattless component variable Q', after filtering by means of the least squares estimation method; ~~it~~ method. It can clearly be seen that the 50 Hz components have been removed.

30

As shown in Figure 2, after the filtering in the unit 9, phase resistance values R and phase reactance values X are determined in accordance with equation (4), and the phase impedance values $Z=R+jX$ determined from them are emitted at the output of the impedance determination unit Ib.

35

$$R=P'/I^2, \quad X=Q'/I^2, \quad (4)$$

_____ A least squares estimation method using a signal model in accordance with equation (5) is applied separately to each of the variables P, Q and I^2 in order to filter out the 50 Hz components contained in the phase real power variable P, in the phase Wattless component variable Q and in the squared phase current amplitude variable I^2 .

$$y_k = A \cdot e^{-\frac{t}{\tau}} \cdot \sin(\omega_0 k \cdot T_A) + B \cdot e^{-\frac{t}{\tau}} \cdot \cos(\omega_0 k \cdot T_A) + C \quad (5)$$

_____ The estimation method uses the squared phase current amplitude variable I^2 , the phase real power variable P and the phase Wattless component variable Q to calculate the parameters A, B and C in the signal model. The parameter C gives the sought magnitude of the phase real power variable P' , of the phase Wattless component variable Q' and of the squared phase current amplitude variable I^2 . The summands with the parameters A and B model the 50 Hz components. The variable ω_0 is the frequency (50 Hz) to be filtered out, and T_A is the sampling time.

_____ If an equivalent circuit with only two generator machines at the ends of a power transmission line is considered for the power supply system, the amplitude of the 50 Hz components decays with the time constants τ of the sum impedance between the two generator machines in accordance with equation (6), where L is the loop inductance and R is the loop resistance of the circuit which is closed via the two generator machines.

$$\tau = \frac{\sum L}{\sum R} \quad (6)$$

_____The coefficients A, B and C are determined such that the sum of the squares of the errors between values y determined from the phase current and phase voltage sample values i and u and the sample values y_k calculated in accordance with equation (5) becomes a minimum (see equation (7)).

$$J = \sum_{i=k-N}^k (y_i - h(\underline{\Theta}_k))^2 \rightarrow \text{MIN} \quad (7)$$

10 _____In equation (7), J represents the Q-criterion to be minimized. The signal model included in equation (5) is used as the function h(Θ_k). The parameters A, B and C to be determined form a vector Θ_k in accordance with equation (8).

15

$$\underline{\Theta}_k = \begin{pmatrix} A \\ B \\ C \end{pmatrix} \quad (8)$$

_____The Q-criterion J is derived based on the parameter vector Θ_k in order to solve the minimization task. For the signal model in accordance with equation (5), this then results in equation (9) together with equation (10).

20

$$0 = \sum_{i=k-N}^k 2\underline{\gamma}_i^T (y_i - \underline{\gamma}_i \underline{\Theta}_k) \quad (9)$$

$$\underline{\gamma}_i^k = \frac{\partial h}{\partial \underline{\Theta}_k} \quad \underline{\gamma}_i^k = \begin{pmatrix} \sin\left(\frac{2\pi}{T} i T_A\right) \cdot e^{\frac{i T_A}{\tau}} \\ \cos\left(\frac{2\pi}{T} i T_A\right) \cdot e^{\frac{i T_A}{\tau}} \\ 1 \end{pmatrix} \quad (10)$$

_____ If equation (9) is solved for the vector $\underline{\Theta}_k$, then this results in equation (11), by means of which, and using the matrix \underline{S}_k included in equations (12) and (13), the vector $\underline{\Theta}_k$ is determined.

5

$$\underline{\Theta}_k = \underline{S}_k^{-1} \sum_{i=1}^k \underline{\gamma}_i^T \underline{y}_i \quad (11)$$

$$\underline{S}_k = \sum_{i=k-N}^k \underline{\gamma}_i^T \underline{\gamma}_i \quad (12)$$

$$\underline{S}_k = \begin{pmatrix} \sin^2\left(\frac{2\pi}{T}iT_A\right) \cdot e^{-\frac{iT_A}{\tau}} & \sin\left(\frac{2\pi}{T}iT_A\right)\cos\left(\frac{2\pi}{T}iT_A\right) \cdot e^{-\frac{iT_A}{\tau}} & \sin\left(\frac{2\pi}{T}iT_A\right) \cdot e^{-\frac{iT_A}{\tau}} \\ \cos\left(\frac{2\pi}{T}iT_A\right)\sin\left(\frac{2\pi}{T}iT_A\right) \cdot e^{-\frac{iT_A}{\tau}} & \cos^2\left(\frac{2\pi}{T}iT_A\right) \cdot e^{-\frac{iT_A}{\tau}} & \cos\left(\frac{2\pi}{T}iT_A\right) \cdot e^{-\frac{iT_A}{\tau}} \\ \sin\left(\frac{2\pi}{T}iT_A\right) \cdot e^{-\frac{iT_A}{\tau}} & \cos\left(\frac{2\pi}{T}iT_A\right) \cdot e^{-\frac{iT_A}{\tau}} & 1 \end{pmatrix} \quad (13)$$

_____ Of the parameters A, B and C ~~contained~~included in the vector $\underline{\Theta}_k$, only the parameter C is evaluated. The
10 vectors $\underline{\gamma}_i^k$ in accordance with equation (10) and the matrix \underline{S}_k in accordance with equation (13) are calculated and are stored as constants, so that they are available ~~every time~~when the method is used.

15 _____ Monotony criteria are applied to the locus curves of the impedance values in the impedance plane in the oscillation identification unit Pe, in order to identify the oscillation process. This method for identification of the oscillation process is ~~known per~~
20 ~~se, and is~~ described in German Patent DE 197 46 719 C1.

_____ The oscillation signal resetting unit Pü determines whether an oscillation which has already been identified is still continuing. The procedure used
25 for this purpose comprises the production of an oscillation model for phase impedance values Z associated with the oscillation. A check is then carried out to determine whether the locus curve which is described by the newly determined phase impedance

values Z still corresponds to the oscillation model. When producing the oscillation model, it is assumed that the locus curve is free of discontinuities, and that its direction changes ~~only~~ very slowly. In the present exemplary embodiment, the locus curve is described by a first order power function, that is to say by a linear equation, in accordance with equation (14).

$$X(R) = m \cdot R + X_0 \quad (14)$$

The parameters m and X_0 are determined by means of a non-recursive least squares estimation method from the last N determined phase impedance values Z .

The linear equation is used as a model rule for the least squares estimation method, with the parameter m characterizing the gradient, and the parameter X_0 characterizing the offset of the linear equation. The parameters m and X_0 for the model in accordance with equation (14) are determined from the last determined value pairs (R_i, X_i) of the phase impedance values Z_i such that the sum of the squares of the errors between the values X_i determined from the measured phase current and phase voltage sample values i and u and the values X calculated in accordance with equation (14) is a minimum (see equation (15)).

$$J = \sum_{i=k-N}^k (X_i - h(\underline{\Theta}_k))^2 \rightarrow \text{MIN} \quad (15)$$

In equation (15), J is the Q-criterion to be minimized, the model rule in accordance with equation (14) is used as the function $h(\underline{\Theta}_k)$. In accordance with equation (16), the parameter vector $\underline{\Theta}_k$ contains the parameters m and X_0 , to be determined, from the model rule.

$$\underline{\Theta}_k = \begin{pmatrix} m \\ X_0 \end{pmatrix} \quad (16)$$

_____ In order to solve the minimization task, the Q-criterion J ~~must be~~ is derived on the basis of the parameter vector $\underline{\Theta}_k$. The following equations (17) and (18) are then obtained for the signal model in accordance with equation (14):

$$0 = \sum_{i=k-N}^k 2\underline{\gamma}_i^T (X_i - h(\underline{\Theta}_k)_i) \quad (17)$$

$$\underline{\gamma}_i^k = \frac{\partial h}{\partial \underline{\Theta}_k} = \begin{pmatrix} R \\ 1 \end{pmatrix} \quad (18)$$

10

_____ If equation (17) is solved for the parameter vector $\underline{\Theta}_k$, then this results in equation (19) for determining the parameter vector $\underline{\Theta}_k$.

$$\underline{\Theta}_k = \underline{S}_k^{-1} \sum_{i=1}^k \underline{\gamma}_i^T y_i \quad (19)$$

15

where

$$\underline{S}_k = \sum_{i=k-N}^k \underline{\gamma}_i^T \underline{\gamma}_i \quad (20)$$

$$\underline{S}_k = \sum_{i=k-N}^k \begin{pmatrix} R_i^2 & R_i \\ R_i & 1 \end{pmatrix} \quad (21)$$

20

_____ After substitution of the parameters in equation (14), this ~~thus~~ results in the estimated oscillation model. If a newly determined phase impedance value Z corresponds to the oscillation model, ~~that is to say~~ model. That is, it is within a tolerance band around the linear equation represented by equation (14), then this identifies that the oscillation is continuing. If the newly determined phase impedance value Z is outside the tolerance band, then this identifies that the oscillation has stopped, and an oscillation reset signal Pr is emitted at the output of

25

the oscillation signal resetting unit P_ü for the memory element Sp₁, Sp₂ or Sp₃ for the respective phase.

_____The phase selection unit Pa receives a stimulus
5 from, for example, a distance protection device which
is not illustrated. Depending on the nature of the
stimulated loop, it determines the phases for which the
oscillation identification unit Pe and/or the
oscillation signal resetting unit P_ü should investigate
10 the oscillation behavior. The following table shows the
association between the stimulated loops and the
phases.

Stimulated loops	Phases to be investigated for oscillation behavior
L1E	L1
L2E	L2
L3E	L3
L12	L1 and L2
L23	L2 and L3
L31	L1 and L3